LM258, LM358, LM358A, LM358E, LM2904, LM2904A, LM2904E, LM2904V, NCV2904

Single Supply Dual Operational Amplifiers

Utilizing the circuit designs perfected for Quad Operational Amplifiers, these dual operational amplifiers feature low power drain, a common mode input voltage range extending to ground/V_{EE}, and single supply or split supply operation. The LM358 series is equivalent to one−half of an LM324.


These amplifiers have several distinct advantages over standard operational amplifier types in single supply applications. They can operate at supply voltages as low as 3.0 V or as high as 32 V, with quiescent currents about one−fifth of those associated with the MC1741 (on a per amplifier basis). The common mode input range includes the negative supply, thereby eliminating the necessity for external biasing components in many applications. The output voltage range also includes the negative power supply voltage.

Features

- Short Circuit Protected Outputs
- True Differential Input Stage
- Single Supply Operation: 3.0 V to 32 V
- Low Input Bias Currents
- Internally Compensated
- Common Mode Range Extends to Negative Supply
- Single and Split Supply Operation
- ESD Clamps on the Inputs Increase Ruggedness of the Device without Affecting Operation
- NCV Prefix for Automotive and Other Applications Requiring Unique Site and Control Change Requirements; AEC−Q100 Qualified and PPAP Capable
- These Devices are Pb−Free, Halogen Free/BFR Free and are RoHS Compliant

ON Semiconductor®


www.onsemi.com



PDIP−8
N, AN, VN SUFFIX
CASE 626




SOIC−8
D, VD SUFFIX
CASE 751



Micro8™
DMR2 SUFFIX
CASE 846A

PIN CONNECTIONS



(Top View)


ORDERING INFORMATION

See detailed ordering and shipping information in the package dimensions section on page 10 of this data sheet.


DEVICE MARKING INFORMATION

See general marking information in the device marking section on page 11 of this data sheet.

© Semiconductor Components Industries, LLC, 2016



Single Supply



Split Supplies

Figure 1.




Figure 2. Representative Schematic Diagram
(One−Half of Circuit Shown)

MAXIMUM RATINGS (T_A = +25°C, unless otherwise noted.)

Rating		Symbol	Value	Unit
Power Supply Voltages Single Supply Split Supplies		 V_{CC} V_{CC}, V_{EE}	 32 ±16	Vdc
Input Differential Voltage Range (Note 1)		V_{IDR}	±32	Vdc
Input Common Mode Voltage Range		V_{ICR}	−0.3 to 32	Vdc
Output Short Circuit Duration		t_{SC}	Continuous	
Junction Temperature		T_J	150	°C
Thermal Resistance, Junction−to−Air (Note 2)	Case 846A Case 751 Case 626	$R_{\theta JA}$	238 212 161	°C/W
Storage Temperature Range		T_{stg}	−65 to +150	°C
Operating Ambient Temperature Range	 LM258 LM358, LM358A, LM358E LM2904, LM2904A, LM2904E LM2904V, NCV2904 (Note 3)	T_A	 −25 to +85 0 to +70 −40 to +105 −40 to +125	°C

Stresses exceeding those listed in the Maximum Ratings table may damage the device. If any of these limits are exceeded, device functionality should not be assumed, damage may occur and reliability may be affected.

1. Split Power Supplies.
2. All $R_{\theta JA}$ measurements made on evaluation board with 1 oz. copper traces of minimum pad size. All device outputs were active.
3. *NCV2904 is qualified for automotive use.*

ESD RATINGS

Rating	HBM	MM	Unit
ESD Protection at any Pin (Human Body Model − HBM, Machine Model − MM)			
NCV2904 (Note 3)	2000	200	V
LM358E, LM2904E	2000	200	V
LM358DG/DR2G, LM2904DG/DR2G	250	100	V
All Other Devices	2000	200	V

ELECTRICAL CHARACTERISTICS (V_{CC} = 5.0 V, V_{EE} = GND, T_A = 25°C, unless otherwise noted.)

Characteristic	Symbol	LM258			LM358, LM358E			LM358A			Unit
		Min	Typ	Max	Min	Typ	Max	Min	Typ	Max	
Input Offset Voltage V_{CC} = 5.0 V to 30 V, V_{IC} = 0 V to V_{CC} −1.7 V, $V_O \simeq$ 1.4 V, R_S = 0 Ω	V_{IO}										mV
T_A = 25°C		–	2.0	5.0	–	2.0	7.0	–	2.0	3.0	
T_A = T_{high} (Note 4)		–	–	7.0	–	–	9.0	–	–	5.0	
T_A = T_{low} (Note 4)		–	–	7.0	–	–	9.0	–	–	5.0	
Average Temperature Coefficient of Input Offset Voltage T_A = T_{high} to T_{low} (Note 4)	$\Delta V_{IO}/\Delta T$	–	7.0	–	–	7.0	–	–	7.0	–	μV/°C
Input Offset Current	I_{IO}	–	3.0	30	–	5.0	50	–	5.0	30	nA
T_A = T_{high} to T_{low} (Note 4)		–	–	100	–	–	150	–	–	75	
Input Bias Current	I_{IB}	–	−45	−150	–	−45	−250	–	−45	−100	
T_A = T_{high} to T_{low} (Note 4)		–	−50	−300	–	−50	−500	–	−50	−200	
Average Temperature Coefficient of Input Offset Current T_A = T_{high} to T_{low} (Note 4)	$\Delta I_{IO}/\Delta T$	–	10	–	–	10	–	–	10	–	pA/°C
Input Common Mode Voltage Range (Note 5), V_{CC} = 30 V	V_{ICR}	0	–	28.3	0	–	28.3	0	–	28.5	V
V_{CC} = 30 V, T_A = T_{high} to T_{low}		0	–	28	0	–	28	0	–	28	
Differential Input Voltage Range	V_{IDR}	–	–	V_{CC}	–	–	V_{CC}	–	–	V_{CC}	V
Large Signal Open Loop Voltage Gain	A_{VOL}										V/mV
R_L = 2.0 kΩ, V_{CC} = 15 V, For Large V_O Swing,		50	100	–	25	100	–	25	100	–	
T_A = T_{high} to T_{low} (Note 4)		25	–	–	15	–	–	15	–	–	
Channel Separation 1.0 kHz ≤ f ≤ 20 kHz, Input Referenced	CS	–	−120	–	–	−120	–	–	−120	–	dB
Common Mode Rejection R_S ≤ 10 kΩ	CMR	70	85	–	65	70	–	65	70	–	dB
Power Supply Rejection	PSR	65	100	–	65	100	–	65	100	–	dB
Output Voltage−High Limit T_A = T_{high} to T_{low} (Note 4)	V_{OH}										V
V_{CC} = 5.0 V, R_L = 2.0 kΩ, T_A = 25°C		3.3	3.5	–	3.3	3.5	–	3.3	3.5	–	
V_{CC} = 30 V, R_L = 2.0 kΩ		26	–	–	26	–	–	26	–	–	
V_{CC} = 30 V, R_L = 10 kΩ		27	28	–	27	28	–	27	28	–	
Output Voltage−Low Limit V_{CC} = 5.0 V, R_L = 10 kΩ, T_A = T_{high} to T_{low} (Note 4)	V_{OL}	–	5.0	20	–	5.0	20	–	5.0	20	mV
Output Source Current	I_{O+}										mA
V_{ID} = +1.0 V, V_{CC} = 15 V		20	40	–	20	40	–	20	40	–	
T_A = T_{high} to T_{low} (LM358A Only)								10	–	–	
Output Sink Current	I_{O-}										
V_{ID} = −1.0 V, V_{CC} = 15 V		10	20	–	10	20	–	10	20	–	mA
T_A = T_{high} to T_{low} (LM358A Only)								5.0	–	–	mA
V_{ID} = −1.0 V, V_O = 200 mV		12	50	–	12	50	–	12	50	–	μA
Output Short Circuit to Ground (Note 6)	I_{SC}	–	40	60	–	40	60	–	40	60	mA
Power Supply Current (Total Device) T_A = T_{high} to T_{low} (Note 4)	I_{CC}										mA
V_{CC} = 30 V, V_O = 0 V, R_L = ∞		–	1.5	3.0	–	1.5	3.0	–	1.5	2.0	
V_{CC} = 5 V, V_O = 0 V, R_L = ∞		–	0.7	1.2	–	0.7	1.2	–	0.7	1.2	

4. LM258: T_{low} = −25°C, T_{high} = +85°C
   LM2904/A/E: T_{low} = −40°C, T_{high} = +105°C
   NCV2904 is qualified for automotive use.
   LM358, LM358A, LM358E: T_{low} = 0°C, T_{high} = +70°C
   LM2904V & NCV2904: T_{low} = −40°C, T_{high} = +125°C
5. The input common mode voltage or either input signal voltage should not be allowed to go negative by more than 0.3 V. The upper end of the common mode voltage range is V_{CC} − 1.7 V.
6. Short circuits from the output to V_{CC} can cause excessive heating and eventual destruction. Destructive dissipation can result from simultaneous shorts on all amplifiers.

ELECTRICAL CHARACTERISTICS (V_{CC} = 5.0 V, V_{EE} = Gnd, T_A = 25°C, unless otherwise noted.)

Characteristic	Symbol	LM2904/LM2904E			LM2904A			LM2904V, NCV2904			Unit
		Min	Typ	Max	Min	Typ	Max	Min	Typ	Max	
Input Offset Voltage V_{CC} = 5.0 V to 30 V, V_{IC} = 0 V to V_{CC} −1.7 V, $V_O \simeq$ 1.4 V, R_S = 0 Ω	V_{IO}										mV
T_A = 25°C		–	2.0	7.0	–	2.0	7.0	–	–	7.0	
$T_A = T_{high}$ (Note 7)		–	–	10	–	–	10	–	–	13	
$T_A = T_{low}$ (Note 7)		–	–	10	–	–	10	–	–	10	
Average Temperature Coefficient of Input Offset Voltage $T_A = T_{high}$ to T_{low} (Note 7)	$\Delta V_{IO}/\Delta T$	–	7.0	–	–	7.0	–	–	7.0	–	μV/°C
Input Offset Current	I_{IO}	–	5.0	50	–	5.0	50	–	5.0	50	nA
$T_A = T_{high}$ to T_{low} (Note 7)		–	45	200	–	45	200	–	45	200	
Input Bias Current	I_{IB}	–	−45	−250	–	−45	−100	–	−45	−250	
$T_A = T_{high}$ to T_{low} (Note 7)		–	−50	−500	–	−50	−250	–	−50	−500	
Average Temperature Coefficient of Input Offset Current $T_A = T_{high}$ to T_{low} (Note 7)	$\Delta I_{IO}/\Delta T$	–	10	–	–	10	–	–	10	–	pA/°C
Input Common Mode Voltage Range (Note 8), V_{CC} = 30 V	V_{ICR}	0	–	28.3	0	–	28.3	0	–	28.3	V
V_{CC} = 30 V, $T_A = T_{high}$ to T_{low}		0	–	28	0	–	28	0	–	28	
Differential Input Voltage Range	V_{IDR}	–	–	V_{CC}	–	–	V_{CC}	–	–	V_{CC}	V
Large Signal Open Loop Voltage Gain	A_{VOL}										V/mV
R_L = 2.0 kΩ, V_{CC} = 15 V, For Large V_O Swing,		25	100	–	25	100	–	25	100	–	
$T_A = T_{high}$ to T_{low} (Note 7)		15	–	–	15	–	–	15	–	–	
Channel Separation 1.0 kHz ≤ f ≤ 20 kHz, Input Referenced	CS	–	−120	–	–	−120	–	–	−120	–	dB
Common Mode Rejection R_S ≤ 10 kΩ	CMR	50	70	–	50	70	–	50	70	–	dB
Power Supply Rejection	PSR	50	100	–	50	100	–	50	100	–	dB
Output Voltage−High Limit $T_A = T_{high}$ to T_{low} (Note 7)	V_{OH}										V
V_{CC} = 5.0 V, R_L = 2.0 kΩ, T_A = 25°C		3.3	3.5	–	3.3	3.5	–	3.3	3.5	–	
V_{CC} = 30 V, R_L = 2.0 kΩ		26	–	–	26	–	–	26	–	–	
V_{CC} = 30 V, R_L = 10 kΩ		27	28	–	27	28	–	27	28	–	
Output Voltage−Low Limit V_{CC} = 5.0 V, R_L = 10 kΩ, $T_A = T_{high}$ to T_{low} (Note 7)	V_{OL}	–	5.0	20	–	5.0	20	–	5.0	20	mV
Output Source Current V_{ID} = +1.0 V, V_{CC} = 15 V	I_{O+}	20	40	–	20	40	–	20	40	–	mA
Output Sink Current	I_{O-}										
V_{ID} = −1.0 V, V_{CC} = 15 V		10	20	–	10	20	–	10	20	–	mA
V_{ID} = −1.0 V, V_O = 200 mV		–	–	–	–	–	–	–	–	–	μA
Output Short Circuit to Ground (Note 9)	I_{SC}	–	40	60	–	40	60	–	40	60	mA
Power Supply Current (Total Device) $T_A = T_{high}$ to T_{low} (Note 7)	I_{CC}										mA
V_{CC} = 30 V, V_O = 0 V, R_L = ∞		–	1.5	3.0	–	1.5	3.0	–	1.5	3.0	
V_{CC} = 5 V, V_O = 0 V, R_L = ∞		–	0.7	1.2	–	0.7	1.2	–	0.7	1.2	

7. LM258: T_{low} = −25°C, T_{high} = +85°C
   LM358, LM358A, LM358E: T_{low} = 0°C, T_{high} = +70°C
   LM2904/A/E: T_{low} = −40°C, T_{high} = +105°C
   LM2904V & NCV2904: T_{low} = −40°C, T_{high} = +125°C
   NCV2904 is qualified for automotive use.
8. The input common mode voltage or either input signal voltage should not be allowed to go negative by more than 0.3 V. The upper end of the common mode voltage range is V_{CC} − 1.7 V.
9. Short circuits from the output to V_{CC} can cause excessive heating and eventual destruction. Destructive dissipation can result from simultaneous shorts on all amplifiers.

Product parametric performance is indicated in the Electrical Characteristics for the listed test conditions, unless otherwise noted. Product performance may not be indicated by the Electrical Characteristics if operated under different conditions.

CIRCUIT DESCRIPTION

The LM358 series is made using two internally compensated, two−stage operational amplifiers. The first stage of each consists of differential input devices Q20 and Q18 with input buffer transistors Q21 and Q17 and the differential to single ended converter Q3 and Q4. The first stage performs not only the first stage gain function but also performs the level shifting and transconductance reduction functions. By reducing the transconductance, a smaller compensation capacitor (only 5.0 pF) can be employed, thus saving chip area. The transconductance reduction is accomplished by splitting the collectors of Q20 and Q18. Another feature of this input stage is that the input common mode range can include the negative supply or ground, in single supply operation, without saturating either the input devices or the differential to single−ended converter. The second stage consists of a standard current source load amplifier stage.

Each amplifier is biased from an internal−voltage regulator which has a low temperature coefficient thus giving each amplifier good temperature characteristics as well as excellent power supply rejection.




Figure 3. Large Signal Voltage Follower Response




Figure 4. Input Voltage Range




Figure 5. Large−Signal Open Loop Voltage Gain




Figure 6. Large−Signal Frequency Response




Figure 7. Small Signal Voltage Follower Pulse Response (Noninverting)




Figure 8. Power Supply Current versus Power Supply Voltage




Figure 9. Input Bias Current versus Supply Voltage




Figure 10. Voltage Reference




Figure 11. Wien Bridge Oscillator




Figure 12. High Impedance Differential Amplifier




Figure 13. Comparator with Hysteresis






Figure 14. Bi−Quad Filter



$$f = \frac{R1 + R_C}{4\,CR_f\,R1} \quad \text{if,} \quad R3 = \frac{R2\,R1}{R2 + R1}$$

Figure 15. Function Generator



Given: f_o = center frequency

$A(f_o)$ = gain at center frequency

Choose value f_o, C

Then: $R3 = \frac{Q}{\pi\, f_o\, C}$

$$R1 = \frac{R3}{2\,A(f_o)}$$

$$R2 = \frac{R1\,R3}{4Q^2\,R1 - R3}$$

For less than 10% error from operational amplifier. $\frac{Q_o\, f_o}{BW} < 0.1$

Where f_o and BW are expressed in Hz.

If source impedance varies, filter may be preceded with voltage follower buffer to stabilize filter parameters.

Figure 16. Multiple Feedback Bandpass Filter

ORDERING INFORMATION


Device	Operating Temperature Range	Package	Shipping†
LM358ADR2G	0°C to +70°C	SOIC−8 (Pb−Free)	2500 / Tape & Reel
LM358DG			98 Units / Rail
LM358DR2G			2500 / Tape & Reel
LM358EDR2G		SOIC−8 (Pb−Free)	2500 / Tape & Reel
LM358DMR2G		Micro8 (Pb−Free)	4000 / Tape & Reel
LM358NG		PDIP−8 (Pb−Free)	50 Units / Rail
LM258DG	−25°C to +85°C	SOIC−8 (Pb−Free)	98 Units / Rail
LM258DR2G			2500 / Tape & Reel
LM258DMR2G		Micro8 (Pb−Free)	4000 / Tape & Reel
LM258NG		PDIP−8 (Pb−Free)	50 Units / Rail
LM2904DG	−40°C to +105°C	SOIC−8 (Pb−Free)	98 Units / Rail
LM2904DR2G			2500 / Tape & Reel
LM2904EDR2G		SOIC−8 (Pb−Free)	2500 / Tape & Reel
LM2904DMR2G		Micro8 (Pb−Free)	2500 / Tape & Reel
LM2904NG		PDIP−8 (Pb−Free)	50 Units / Rail
LM2904ADMG		Micro8 (Pb−Free)	4000 / Tape & Reel
LM2904ADMR2G			4000 / Tape & Reel
LM2904ANG		PDIP−8 (Pb−Free)	50 Units / Rail
LM2904VDG	−40°C to +125°C	SOIC−8 (Pb−Free)	98 Units / Rail
LM2904VDR2G			2500 / Tape & Reel
LM2904VDMR2G		Micro8 (Pb−Free)	4000 / Tape & Reel
LM2904VNG		PDIP−8 (Pb−Free)	50 Units / Rail
NCV2904DR2G*		SOIC−8 (Pb−Free)	2500 / Tape & Reel
NCV2904DMR2G*		Micro8 (Pb−Free)	4000 / Tape & Reel

†For information on tape and reel specifications, including part orientation and tape sizes, please refer to our Tape and Reel Packaging Specifications Brochure, BRD8011/D.


*NCV Prefix for Automotive and Other Applications Requiring Unique Site and Control Change Requirements; AEC−Q100 Qualified and PPAP Capable.

MARKING DIAGRAMS


PDIP−8
N SUFFIX
CASE 626




PDIP−8
AN SUFFIX
CASE 626




PDIP−8
VN SUFFIX
CASE 626




SOIC−8
D SUFFIX
CASE 751



SOIC−8
VD SUFFIX
CASE 751



Micro8
DMR2 SUFFIX
CASE 846A




*This diagram also applies to NCV2904

x = 2 or 3
A = Assembly Location
WL, L = Wafer Lot
YY, Y = Year
WW, W = Work Week
G = Pb−Free Package
▪ = Pb−Free Package − (Note: Microdot may be in either location)

PACKAGE DIMENSIONS

PDIP−8
N, AN, VN SUFFIX
CASE 626−05
ISSUE P




NOTES:
1. DIMENSIONING AND TOLERANCING PER ASME Y14.5M, 1994.
2. CONTROLLING DIMENSION: INCHES.
3. DIMENSIONS A, A1 AND L ARE MEASURED WITH THE PACKAGE SEATED IN JEDEC SEATING PLANE GAUGE GS−3.
4. DIMENSIONS D, D1 AND E1 DO NOT INCLUDE MOLD FLASH OR PROTRUSIONS. MOLD FLASH OR PROTRUSIONS ARE NOT TO EXCEED 0.10 INCH.
5. DIMENSION E IS MEASURED AT A POINT 0.015 BELOW DATUM PLANE H WITH THE LEADS CONSTRAINED PERPENDICULAR TO DATUM C.
6. DIMENSION eB IS MEASURED AT THE LEAD TIPS WITH THE LEADS UNCONSTRAINED.
7. DATUM PLANE H IS COINCIDENT WITH THE BOTTOM OF THE LEADS, WHERE THE LEADS EXIT THE BODY.
8. PACKAGE CONTOUR IS OPTIONAL (ROUNDED OR SQUARE CORNERS).

	INCHES		MILLIMETERS	
DIM	MIN	MAX	MIN	MAX
A	----	0.210	---	5.33
A1	0.015	----	0.38	---
A2	0.115	0.195	2.92	4.95
b	0.014	0.022	0.35	0.56
b2	0.060 TYP		1.52 TYP	
C	0.008	0.014	0.20	0.36
D	0.355	0.400	9.02	10.16
D1	0.005	----	0.13	---
E	0.300	0.325	7.62	8.26
E1	0.240	0.280	6.10	7.11
e	0.100 BSC		2.54 BSC	
eB	----	0.430	---	10.92
L	0.115	0.150	2.92	3.81
M	----	10°	---	10°

PACKAGE DIMENSIONS


SOIC−8 NB
CASE 751−07
ISSUE AK



NOTES:
1. DIMENSIONING AND TOLERANCING PER ANSI Y14.5M, 1982.
2. CONTROLLING DIMENSION: MILLIMETER.
3. DIMENSION A AND B DO NOT INCLUDE MOLD PROTRUSION.
4. MAXIMUM MOLD PROTRUSION 0.15 (0.006) PER SIDE.
5. DIMENSION D DOES NOT INCLUDE DAMBAR PROTRUSION. ALLOWABLE DAMBAR PROTRUSION SHALL BE 0.127 (0.005) TOTAL IN EXCESS OF THE D DIMENSION AT MAXIMUM MATERIAL CONDITION.
6. 751−01 THRU 751−06 ARE OBSOLETE. NEW STANDARD IS 751−07.

	MILLIMETERS		INCHES	
DIM	MIN	MAX	MIN	MAX
A	4.80	5.00	0.189	0.197
B	3.80	4.00	0.150	0.157
C	1.35	1.75	0.053	0.069
D	0.33	0.51	0.013	0.020
G	1.27 BSC		0.050 BSC	
H	0.10	0.25	0.004	0.010
J	0.19	0.25	0.007	0.010
K	0.40	1.27	0.016	0.050
M	0 °	8 °	0 °	8 °
N	0.25	0.50	0.010	0.020
S	5.80	6.20	0.228	0.244

SOLDERING FOOTPRINT*




SCALE 6:1 (mm / inches)

*For additional information on our Pb−Free strategy and soldering details, please download the ON Semiconductor Soldering and Mounting Techniques Reference Manual, SOLDERRM/D.

PACKAGE DIMENSIONS


Micro8™
CASE 846A–02
ISSUE J



NOTES:
1. DIMENSIONING AND TOLERANCING PER ANSI Y14.5M, 1982.
2. CONTROLLING DIMENSION: MILLIMETER.
3. DIMENSION A DOES NOT INCLUDE MOLD FLASH, PROTRUSIONS OR GATE BURRS. MOLD FLASH, PROTRUSIONS OR GATE BURRS SHALL NOT EXCEED 0.15 (0.006) PER SIDE.
4. DIMENSION B DOES NOT INCLUDE INTERLEAD FLASH OR PROTRUSION. INTERLEAD FLASH OR PROTRUSION SHALL NOT EXCEED 0.25 (0.010) PER SIDE.
5. 846A–01 OBSOLETE, NEW STANDARD 846A–02.

	MILLIMETERS			INCHES		
DIM	MIN	NOM	MAX	MIN	NOM	MAX
A	––	––	1.10	––	––	0.043
A1	0.05	0.08	0.15	0.002	0.003	0.006
b	0.25	0.33	0.40	0.010	0.013	0.016
c	0.13	0.18	0.23	0.005	0.007	0.009
D	2.90	3.00	3.10	0.114	0.118	0.122
E	2.90	3.00	3.10	0.114	0.118	0.122
e	0.65 BSC			0.026 BSC		
L	0.40	0.55	0.70	0.016	0.021	0.028
H_E	4.75	4.90	5.05	0.187	0.193	0.199

RECOMMENDED SOLDERING FOOTPRINT*



DIMENSION: MILLIMETERS

*For additional information on our Pb–Free strategy and soldering details, please download the ON Semiconductor Soldering and Mounting Techniques Reference Manual, SOLDERRM/D.

Micro8 is a trademark of International Rectifier.

ON Semiconductor and ON are trademarks of Semiconductor Components Industries, LLC dba ON Semiconductor or its subsidiaries in the United States and/or other countries. ON Semiconductor owns the rights to a number of patents, trademarks, copyrights, trade secrets, and other intellectual property. A listing of ON Semiconductor's product/patent coverage may be accessed at www.onsemi.com/site/pdf/Patent–Marking.pdf. ON Semiconductor reserves the right to make changes without further notice to any products herein. ON Semiconductor makes no warranty, representation or guarantee regarding the suitability of its products for any particular purpose, nor does ON Semiconductor assume any liability arising out of the application or use of any product or circuit, and specifically disclaims any and all liability, including without limitation special, consequential or incidental damages. Buyer is responsible for its products and applications using ON Semiconductor products, including compliance with all laws, regulations and safety requirements or standards, regardless of any support or applications information provided by ON Semiconductor. "Typical" parameters which may be provided in ON Semiconductor data sheets and/or specifications can and do vary in different applications and actual performance may vary over time. All operating parameters, including "Typicals" must be validated for each customer application by customer's technical experts. ON Semiconductor does not convey any license under its patent rights nor the rights of others. ON Semiconductor products are not designed, intended, or authorized for use as a critical component in life support systems or any FDA Class 3 medical devices or medical devices with a same or similar classification in a foreign jurisdiction or any devices intended for implantation in the human body. Should Buyer purchase or use ON Semiconductor products for any such unintended or unauthorized application, Buyer shall indemnify and hold ON Semiconductor and its officers, employees, subsidiaries, affiliates, and distributors harmless against all claims, costs, damages, and expenses, and reasonable attorney fees arising out of, directly or indirectly, any claim of personal injury or death associated with such unintended or unauthorized use, even if such claim alleges that ON Semiconductor was negligent regarding the design or manufacture of the part. ON Semiconductor is an Equal Opportunity/Affirmative Action Employer. This literature is subject to all applicable copyright laws and is not for resale in any manner.

PUBLICATION ORDERING INFORMATION

LITERATURE FULFILLMENT:
Literature Distribution Center for ON Semiconductor
19521 E. 32nd Pkwy, Aurora, Colorado 80011 USA
Phone: 303–675–2175 or 800–344–3860 Toll Free USA/Canada
Fax: 303–675–2176 or 800–344–3867 Toll Free USA/Canada
Email: orderlit@onsemi.com

N. American Technical Support: 800–282–9855 Toll Free USA/Canada
Europe, Middle East and Africa Technical Support:
Phone: 421 33 790 2910

ON Semiconductor Website: **www.onsemi.com**

Order Literature: http://www.onsemi.com/orderlit

For additional information, please contact your local Sales Representative